

digitalWrite()

Description

Write a **HIGH** or a **LOW** value to a digital pin.

If the pin has been configured as an OUTPUT with `pinMode()`, its voltage will be set to the corresponding value: 5V (or 3.3V on 3.3V boards) for HIGH, 0V (ground) for LOW.

If the pin is configured as an INPUT, `digitalWrite()` will enable (HIGH) or disable (LOW) the internal pullup on the input pin. It is recommended to set the `pinMode()` to `INPUT_PULLUP` to enable the internal pull-up resistor. See the [digital pins tutorial](#) for more information.

NOTE: If you do not set the `pinMode()` to OUTPUT, and connect an LED to a pin, when calling `digitalWrite(HIGH)`, the LED may appear dim. Without explicitly setting `pinMode()`, `digitalWrite()` will have enabled the internal pull-up resistor, which acts like a large current-limiting resistor.

Syntax

```
digitalWrite(pin, value)
```

Parameters

pin: the pin number

value: **HIGH** or **LOW**

Returns

none

Example

```
int ledPin = 13;           // LED connected to digital pin 13

void setup()
{
  pinMode(ledPin, OUTPUT); // sets the digital pin as output
}

void loop()
{
  digitalWrite(ledPin, HIGH); // sets the LED on
  delay(1000);                // waits for a second
  digitalWrite(ledPin, LOW);  // sets the LED off
  delay(1000);                // waits for a second
}
```

Sets pin 13 to HIGH, makes a one-second-long delay, and sets the pin back to LOW.